



VOLTAGE, CONTINUITY, AND Current tester

FLIR VT8™

The FLIR VT8 is a high-quality voltage, continuity, and current tester, ideal for electricians and service technicians who troubleshoot and verify electrical installations or systems within commercial and light industrial facilities. The FLIR VT8's optimized and open-jaw design allows it to fit into tight spaces and reliably measure large-diameter cables. Extensive measurement features make the FLIR VT8 a versatile tool – just one meter can get the job done. Carry the compact tester in your pocket to be ready at any moment for easy troubleshooting.

Choose from two models: the FLIR VT8-600 with a CAT III-600 V /CAT IV-300 V safety rating and a 100 A/600 V measuring range; or the FLIR VT8-1000 with the CAT III-1000 V/CAT IV-600 V safety rating and a 200 A/1000 V measuring range.

www.flir.com/vt8-series



RUGGED AND SAFE

Made with the quality and reliability you have come to expect from $\ensuremath{\mathsf{FLIR}}$ test and measurement tools

- Work more safely with the CAT IV safety ratings
- Safely store test leads when not in use with the built-in test lead holder
- Keep the test leads out of your way when you're not using them - the length is short enough to minimize interference, yet long enough to get the job done



RICH FEATURES Equipped with the capabilities you need for one versatile troubleshooting tool

- Measure AC/DC voltage and current, continuity, resistance, and capacitance
- Work efficiently in dimly lit areas using the bright LED worklight and backlit display
- Detect live AC voltages with the built-in non-contact voltage (NCV) detector
- Improve accuracy of readings with True RMS measurements



FLEXIBLE, EASY TO USE Designed for long, trouble-free operation so you can focus on the task at hand

- Take measurements in tight spaces with the optimized jaw design, and measure large-diameter cables with the wide jaw opening
- Operate the meter with one hand thanks to the compact, ergonomic design
- View information easily at any distance on the large multi-function LCD display

SPECIFICATIONS

Part Number	VT8-600	VT8-1000
Electrical Measurement		
True RMS Voltage and Current	Yes	
Auto-Ranging	Yes	
AC/DC Current Range	100 A	200 A
AC/DC Current Resolution	0.1 A	
AC (50 to 60 Hz) / DC Current Accuracy	±2.5%	
AC/DC Voltage Range	600 V	1000 V
AC/DC Voltage Resolution	0.1 V	
AC (45 to 66 Hz) / DC Voltage Accuracy	± 1.5%, ±1.0%	
Resistance	60.00 MΩ ± (1.5%)	
Continuity Check Threshold	10 Ω to 100 Ω	
Capacitance	600 μF ±4.0%, 6000 μF ±10.0%	
Non-Contact Voltage Detector (NCV)	≥100 Vrms; ≤10 mm distance (LED/buzzer alerts)	
Additional Measurement Functions	DCA zero, relative mode (AC/DC voltage, AC current, and capacitance), data hold	
General		
Worklights	White LED	
Jaw Opening	15.5 mm (0.61 in)	
Display	6000-count backlit multi-function LCD	
Display Rate	Approximately 3 times per second	
Polarity	Automatic display of positive and negative polarity	
Over-Range Indication	"OL" or "-OL" displayed	
Auto Power Off	After 15 minutes	
Power Source	2 x AA alkaline batteries	
Low battery Indication	Battery symbol is displayed when batteries need changing	
Environmental Data		
Operating Temperature	-10 to 50°C (14	to 122°F)
Relative Humidity	95% max; 5 to 30°C (41 to 86°F) / 75% max; 30 to 40°C (86 to 104°F) / 45% max; 40 to 50°C (104 to 122°F)	
Storage Temperature	-30 to 60°C (-22 to 140°F), batteries not installed	
Drop Test	2 m (6.6 ft)	
Physical Data		
Dimensions: ($W \times H \times D$)	210 mm × 53 mm × 35 mm (8.27 in × 2.1 in × 0.67 in)	
Weight	163.7 g (5.7 oz) including batteries	
General Information		
Warranty	Limited 3-year	
Certifications	C-UL-US, CE, RCM	
Safety Category Rating	CAT IV-300 V	CAT IV-600 V
	CAT III-600 V	CAT III-1000 V
	EN 6101	
	EN 61010-2-032 EN 61010-2-033	



绿测科技有限公司

广州总部:广州市番禺区陈边村金欧大道83号江潮创意园A栋208室 深圳分公司:深圳市龙华区龙华街道油松社区东环一路1号耀丰通工业园1-2栋2栋607 南宁分公司: 广西自由贸易试验区南宁片区五象大道401号五象航洋城1号楼3519号 广州分公司:广州市南沙区凤凰大道89号中国铁建·凤凰广场B栋1201房 电话: 020-2204 2442 传真: 020-8067 2851 邮箱: Sales@greentest.com.cn



微信视频号

绿测科技订阅号

官网: www.greentest.com.cn

绿测工场服务号